



Be Quiet! Pure Loop 120mm - Processor liquid cooling system

(for: AM3 - LGA1155 - AM3+ - LGA2011 - LGA1150 - LGA2011-3 - LGA1151 - LGA2011 (Square ILM) - LGA2011-3 (Square ILM) - AM4 - LGA2066 - LGA1200) - copper - 120 mm - all black

Group	Coolers
Manufacturer	Be Quiet!
Manufacturer item no.	BW005
EAN/UPC	4260052187883

Description

Pure Loop 120mm is the new high-performing and silent All-in-One water cooling unit of be quiet! for price-conscious users without overclocked systems.

Main features

Product Description	be quiet! Pure Loop 120mm processor liquid cooling system
Product Type	Processor liquid cooling system
Colour	All black
Compatibility	Socket AM3, LGA1155 Socket, Socket AM3+, LGA2011 Socket, LGA1150 Socket, LGA2011-3 Socket, LGA1151 Socket, LGA2011 (Square ILM) Socket, LGA2011-3 (Square ILM) Socket, Socket AM4, LGA2066 Socket, LGA1200 Socket
Heatsink Material	Copper
Fan Diameter	120 mm
Fan Height	25 mm
Fan Bearing	Rifle bearing
Rotation Speed	2000 rpm
Noise Level	18.9 - 36.1 dBA
Power Connector	4-pin fan connector
Rated Voltage	12 V
Features	White LEDs, Pulse-width modulation (PWM) support
Weight	780 g

Extended details

General

Product Type	Processor liquid cooling system
Weight	780 g
Shipping Dimensions (WxDxH) / Weight	14 cm x 32.1 cm x 24 cm / 1.66 kg



Colour	All black
Heatsink & Fan	
Compatible With	Socket AM3, LGA1155 Socket, Socket AM3+, LGA2011 Socket, LGA1150 Socket, LGA2011-3 Socket, LGA1151 Socket, LGA2011 (Square ILM) Socket, LGA2011-3 (Square ILM) Socket, Socket AM4, LGA2066 Socket, LGA1200 Socket
Heatsink Material	Copper
Heatsink Dimensions	157 mm x 120 mm x 27 mm
Radiator Material	Aluminium
Fan Diameter	120 mm
Fan Height	25 mm
Fan Bearing	Rifle bearing
Rotation Speed	2000 rpm
Noise Level	18.9 - 36.1 dBA
Power Connector	4-pin fan connector
Rated Voltage	12 V
Rated Current	0.3 A
Cable Length	42 cm
Features	White LEDs, Pulse-width modulation (PWM) support
Manufacturer Warranty	
Service & Support	Limited warranty - 3 years

Technical data © CNET Content Solutions. Subject to technical modifications and errors.